NAVAL POSTGRADUATE SCHOOL Monterey, California





ASYMPTOTIC PROPERTIES OF A SENSOR ALLOCATION MODEL

by

Donald P. Gaver Patricia A. Jacobs Mark Youngren

May 1995

Approved for public release; distribution is unlimited

Prepared for: Institute for Joint Warfare Analysis, Monterey, CA 93943-5000

and

Force Structure, Resources and Assessment Directorate (J8),

The Joint Staff, Washington, DC 20350-5000

DTIC QUALITY INSPECTED 3

NAVAL POSTGRADUATE SCHOOL MONTEREY, CA 93943-5000

Rear Admiral T. A. Mercer Superintendent

Harrison Shull Provost

Narto

This report was prepared for and funded by the Institute for Joint Warfare Analysis, Monterey, CA, and the Force Structure, Resources, and Assessment Directorate (J8), The Joint Staff, Washington DC.

Reproduction of all or part of this report is authorized.

This report was prepared by:

DONALD P. GAVER, JR. Professor of Operations Research	PATRICIA A. JACOBS Professor of Operations Resea	r <u>ch</u>	
MARK YOUNGREN		NTIS DTIC Unani	CRA&I W TAB nounced ication
Assistant Professor of Operations Research			oution / Availability Codes
	D.1	Dist	Avail and/or Special

Reviewed by:

Released by:

PAUL J. MARTO Dean of Research

PETER PURDUE

Professor and Chairman

Department of Operations Research

Form Approved REPORT DOCUMENTATION PAGE OMB No. 0704-0188 Public reporting burden for this collection of information is estimated to average 1 hour per response, including the time for reviewing instructions, searching existing data sources, gathering and maintaining the data needed, and completing and reviewing the collection of information. Send comments regarding this burden estimate or any other aspect of this collection of information, including suggestions for reducing this burden, to Washington Headquarters Services, Directorate for Information Operations and Reports, 1215 Jefferson Davis Highway, Suite 1204, Artington, VA 22202-4302, and to the Office of Management and Budget, Paperwork Reduction Project (0704-0188), Washington, DC 20503. 3. REPORT TYPE AND DATES COVERED 1. AGENCY USE ONLY (Leave blank) 2. REPORT DATE May 1995 Technical 4. TITLE AND SUBTITLE 5. FUNDING NUMBERS Asymptotic Properties of a Sensor Allocation Model RLGPD 6. AUTHOR(S) Donald P. Gaver, Patricia A. Jacobs and Mark Youngren 7. PERFORMING ORGANIZATION NAME(S) AND ADDRESS(ES) 8. PERFORMING ORGANIZATION REPORT NUMBER Naval Postgraduate School NPS-OR-95-002 Monterey, CA 93943 9. SPONSORING / MONITORING AGENCY NAME(S) AND ADDRESS(ES) 10. SPONSORING / MONITORING AGENCY REPORT NUMBER Institute for Joint Warfare Analysis, Monterey, CA 93943-5000 Force Structure, Resources and Assessment Directorate (J8), The Joint Staff, Washington DC, 20350-5000 11. SUPPLEMENTARY NOTES 12a. DISTRIBUTION / AVAILABILITY STATEMENT 12b. DISTRIBUTION CODE Approved for public release; distribution is unlimited. 13. ABSTRACT (Maximum 200 words) A dynamic adaptive protocol for allocating sensor assets to locations where most opponents' assets appear is described, analyzed, and illustrated. 14. SUBJECT TERMS 15. NUMBER OF PAGES adaptive allocation; estimation of the number of binomial trials; normal approximations 16. PRICE CODE

19. SECURITY CLASSIFICATION

Unclassified

OF ABSTRACT

OF REPORT

17. SECURITY CLASSIFICATION

18. SECURITY CLASSIFICATION

Unclassified

OF THIS PAGE

20. LIMITATION OF ABSTRACT

UL

Asymptotic Properties of a Sensor Allocation Model

- D. P. Gaver
- P. A. Jacobs
- M. Youngren

0. Introduction and Summary

Sensor resources are to be allocated among *I* non-overlapping but possibly contiguous geographical locations called *nodes*. Each sensor look at a node results in an observation, with error, of the number of *units* that are at the node. In military applications *units* may be individual assets such as tanks or ships, or possibly small groups organized as platoons or companies and in geographical proximity; in ecological applications, they might be animals, singly or in groups, or particular vegetation types. The observations are then to be used to estimate the numbers of units at each node. The problem is to allocate sensor resources so as to minimize a measure of the error of the estimates, and of the estimate of the sum of the numbers at all nodes. It is assumed that the units remain on the nodes and do not migrate, although for some sensor types the units must be in motion on the node at least some of the time in order for detection to take place.

The objective of this paper is to propose and study adaptive allocation of sensor effort in such a way as to focus the sensor's attention sequentially and purposefully on nodes so as to pay most attention to those nodes about which the greatest uncertainty, or interest, currently prevails. This problem has features in common with adaptive bin-packing problems (cf. Gaver et al., 1995) and adaptive allocation of customers to servers (cf. Gaver et al., 1993).

Numerical examples show that a properly selected sequentially adaptive rule will provide estimates of improved precision.

A related investigation that has recently come to our attention is that by Thompson and Seber (1994). Their procedures can also be analyzed using the methodology proposed in this paper.

1. The Model

There are I nodes. Assume that node i contains r_i units. Sensor resources are allocated to one of the I nodes at times that occur according to a Poisson process with rate λ . The sensor resource is allocated to node i with probability α_i which is tailored to depend on past allocations in a purposeful way. Let $Z_n(i)$ be the nth observation of node i; a simple model is that $\{Z_n(i); n = 1, 2, ...\}$ are iid with binomial distribution with r_i trials and known probability of success p_i which is the probability of unit detection at node i. We assume for illustration that the number of units on a node does not change, although an adaptive scheme of the type proposed should effectively follow changes in node population.

Let $N_i(t)$ be the number of times in [0,t] that node i is observed by a sensor. Let

$$V(i;t) = Z_1(i) + ... + Z_{N_i(t)}(i)$$

be the sum of all the observations during [0,t] for node i.

Under some conditions V(i;t) has a binomial distribution with $N_i(t)r_i$ trials and probability of success p_i , given $N_i(t)$, although this assumption may not be especially accurate in general. Assuming it to be adequate for the moment, an estimate for the number of units at node i based on observations made during [0,t] is

$$\hat{r}_i(t) = \frac{V(i;t)}{N_i(t)p_i} \tag{1.1}$$

with

$$Var[\hat{r}_{i}(t)] = \frac{r_{i}N_{i}(t)p_{i}(1-p_{i})}{N_{i}(t)^{2}p_{i}^{2}}$$
(1.2)

$$= \frac{r_i(1-p_i)}{N_i(t)p_i} \approx \frac{\hat{r}_i(t)(1-p_i)}{N_i(t)p_i} = \frac{V(i;t)(1-p_i)}{N_i(t)^2 p_i^2}.$$
 (1.3)

There has been much statistical attention paid to estimating the number of trials in a binomial distribution, given probability of success; for recent discussion see Hall (1994). Here we use the simplest such estimator.

Now consider the following *adaptive allocation rule*. A sensor resource arriving at time *t* is allocated to node *i* with probability

$$\alpha_{i}(N_{i}(t), V_{i}(t); N(t), V(t)) = \frac{h_{i}(N_{i}(t), V_{i}(t))}{\sum_{j=1}^{I} h_{j}(N_{j}(t), V_{j}(t))}$$
(1.4)

where the h_i are strictly positive sufficiently smooth functions such that $h_i(cpx, cpy) = cph_i(x, y)$.

One possible form for h_i is

$$h_i(x,v) = \left[\frac{a_i}{x} + \frac{v(1-p_i)}{x^2 p_i^2}\right]^{\gamma} \text{ for } \gamma > 0 \text{ and } a_i > 0;$$
 (1.5)

if it is assumed that given $N_i(t)$, $V_i(t)$ is binomially distributed with mean $N_i(t)p_i$, then from (1.3) it follows that for this function h_i , sensor resources tend to be allocated to those nodes for which the variance, and hence its square root, the standard error of the estimated number of units, is the largest; the probability of allocation to the most uncertain node (by this measure) increases rapidly, approaching unity as γ increases. This tends to bring down that standard error quickly, and to equate standard errors of the estimates across nodes. Clearly, alternative measures of overall sensor performance are feasible, and possibly desirable, such as ones that endeavor to equalize fractional or percent error on

nodes, or ones that also respond to an independent measure of importance of the units on a node. Additionally, node contents may be of various types, which can be considered. Thus, the present discussion is of an illustration of an adaptive allocation scheme.

The purposeful allocation of (1.4) introduces dependence between $\{N_i(t); t \geq 0\}$ and $\{V_i(t); t \geq 0\}$. Asymptotic results for the means $E[N_i(t)]$ and $E[V_i(t)]$ as the rate of the Poisson process $\lambda \to \infty$ are obtained in Section 2. It is shown that the purposeful allocation estimate $\hat{r}_i(t)$ is asymptotically unbiased. Section 3 presents results for the asymptotic means for specific form of function h_i (1.5). Section 4 discusses asymptotic results for the second moments of $\{N_i(t); t \geq 0\}$ and $\{V_i(t); t \geq 0\}$ and presents approximate expressions for the $Var[\hat{r}_i(t)]$ and $Var\left[\sum_i \hat{r}_i(t)\right]$.

Section 5 describes a simpler Poisson approximation. Section 6 presents results from simulation experiments.

2. First-Moment Calculations and Asymptotics

Note that for h > 0

$$E[N_i(t+h)|N(t),V(t)] = N_i(t) + \lambda \alpha_i(N,V)h.$$
 (2.1)

Thus

$$E[N_i(t+h)] = E[N_i(t)] + \lambda E[\alpha_i(N,V)h]. \tag{2.2}$$

Assuming derivatives exist, we have

$$\frac{d}{dt}E[N_i(t)] = \lambda E[\alpha_i(N(t), V(t))]. \tag{2.3}$$

Similarly,

$$E[V_i(t+h)|N(t),V(t)] = V_i(t) + \lambda h\alpha_i(N,V)r_ip_i. \tag{2.4}$$

Thus,

$$E[V_i(t+h)] = E[V_i(t)] + \lambda hr_i p_i E[\alpha_i(N,V)h]. \tag{2.5}$$

Assuming derivatives exist, we have

$$\frac{d}{dt}E[V_i(t)] = r_i p_i \lambda E[\alpha_i(N, V)]. \tag{2.6}$$

Assume α_i is of the form (1.4) where h_i is sufficiently smooth with $h_i(c^px, c^py) = c^ph_i(x, y)$ for constants c and $h_i(x, y) > 0$ for all x, y > 0. We have

$$\alpha_{i}(N(t), V(t)) = \frac{h_{i}(N_{i}(t), V_{i}(t))}{\sum_{j} h_{j}(N_{j}(t), V_{j}(t))}$$

$$= \frac{h_{i}(N_{i}(t)/\lambda, V_{i}(t)/\lambda)}{\sum_{j} h_{j}(N_{j}(t)/\lambda, V_{j}(t)/\lambda)}.$$
(2.7)

Assume $\lim_{\lambda \to \infty} N_i(t)/\lambda = m_i(t)$, $\lim_{\lambda \to \infty} V_i(t)/\lambda = v_i(t)$, $\lim_{\lambda \to \infty} \frac{d}{dt} E[N_i(t)/\lambda] = \frac{d}{dt} m_i(t)$, and $\lim_{\lambda \to \infty} \frac{d}{dt} E[V_i(t)/\lambda] = \frac{d}{dt} v_i(t)$.

Dividing both sides of (2.3) and (2.6) by λ and letting $\lambda \to \infty$, the bounded convergence theorem yields

$$\frac{d}{dt}m_{i}(t) = \frac{h_{i}(m_{i}(t), v_{i}(t))}{\sum_{j} h_{j}(m_{j}(t), v_{j}(t))}.$$
(2.8)

and

$$\frac{d}{dt}v_i(t) = r_i p_i \frac{h_i(m_i(t), v_i(t))}{\sum_j h_j(m_j(t), v_j(t))}$$
(2.9)

Thus,

$$v_i(t) = r_i p_i m_i(t). \tag{2.10}$$

3. Purposeful Allocation

The equations for $m_i(t)$, (2.8), can be solved for special functions h_i . For example, assume

$$h_i(x,y) = \left[\frac{a_i}{x} + \frac{y(1-p_i)}{x^2 p_i^2}\right]^{\gamma} \quad \text{for } \gamma \ge 0 \text{ and } a_i > 0.$$
 (3.1)

Since

$$v_{i}(t) = m_{i}(t)r_{i}p_{i},$$

$$h_{i}(m_{i}(t), v_{i}(t)) = \left[\frac{a_{i}}{m_{i}(t)} + \frac{r_{i}(1 - p_{i})}{m_{i}(t)p_{i}}\right]^{\gamma}.$$
(3.2)

In this case (2.8) can be rewritten as

$$\frac{\frac{d}{dt}m_i(t)}{\frac{d}{dt}m_j(t)} = \left[\frac{a_i + r_ic_i}{a_j + r_jc_j}\frac{m_j(t)}{m_i(t)}\right]^{\gamma}$$
(3.3)

where $c_i = (1 - p_i)/p_i$.

The functions

$$m_i(t) = K(a_i + r_i c_i)^{\gamma/(\gamma + 1)} t$$
(3.4)

with

$$K = \left[\sum_{i=1}^{I} (a_i + r_i c_i)^{\gamma/(\gamma+1)}\right]^{-1}$$
(3.5)

are a solution to (2.8).

Thus, in the limit as $t \to \infty$, the probability that a sensor resource at time t looks at node i is

$$\alpha_i = \frac{\left(a_i + r_i c_i\right)^{\gamma/(\gamma+1)}}{\sum_j \left(a_j + r_j c_j\right)^{\gamma/(\gamma+1)}}.$$
(3.6)

If $\gamma = 0$, then

$$\alpha_i = 1/I \tag{3.7}$$

and the allocation is equally likely.

If $\gamma \rightarrow \infty$, then

$$\alpha_i = \frac{a_i + r_i c_i}{\sum_j a_j + r_j c_j}.$$
 (3.8)

If, further, the probability of detection on node i, p_i , is constant for all the nodes, then the probabilistic allocation for $\gamma \rightarrow \infty$ is roughly proportional to the number of units on the node.

4. Scaling and Approximate Variances of Estimators

Let

$$X_{j}(t) = \frac{N_{j}(t) - \lambda m_{j}(t)}{\sqrt{\lambda}}$$
(4.1)

$$Y_j(t) = \frac{V_j(t) - \lambda v_j(t)}{\sqrt{\lambda}}$$
 (4.2)

In Appendix A, moment generating functions are used to show the asymptotic normality of $\{(X_j(t), Y_j(t)); t \ge 0\}$ as $\lambda \to \infty$. Further, differential equations for their second moments are obtained.

Rewriting

$$N_{i}(t) = \lambda m_{i}(t) + \sqrt{\lambda} X_{i}(t)$$
 (4.3)

$$V_{j}(t) = \lambda v_{j}(t) + \sqrt{\lambda} Y_{j}(t)$$
(4.4)

An approximate variance of the estimator of the number of units on node i,

$$\hat{r}_{i}(t) = \frac{V_{i}(t)}{N_{i}(t)} \frac{1}{p_{i}}$$
(4.5)

can be computed using the "delta method" as follows; cf. Bickel and Doksum (1977). To begin,

$$Var[\hat{r}_i(t)] = \frac{1}{p_i^2} Var\left[\frac{V_i(t)}{N_i(t)}\right]. \tag{4.6}$$

A Taylor expansion yields

$$\frac{V_{i}(t)}{N_{i}(t)} = \frac{v_{i}(t) + Y_{i}(t)/\sqrt{\lambda}}{m_{i}(t) + X_{i}(t)/\sqrt{\lambda}}$$

$$= \frac{v_{i}(t)}{m_{i}(t)} + \frac{1}{m_{i}(t)} \left[Y_{i}(t)/\sqrt{\lambda} \right] - \frac{v_{i}(t)}{m_{i}(t)^{2}} \left(X_{i}(t)/\sqrt{\lambda} \right)$$

$$+ O\left(\frac{1}{\lambda}\right). \tag{4.7}$$

Thus,

$$Var\left[\frac{V_{i}(t)}{N_{i}(t)}\right] \approx E\left[\left(\frac{V_{i}(t)}{N_{i}(t)} - \frac{v_{i}(t)}{m_{i}(t)}\right)^{2}\right]$$

$$\approx \frac{1}{\lambda m_{i}(t)^{2}} \left\{ E\left[Y_{i}^{2}(t)\right] + \left[\frac{v_{i}(t)}{m_{i}(t)}\right]^{2} E\left[X_{i}^{2}(t)\right] - 2\frac{v_{i}(t)}{m_{i}(t)} E\left[Y_{i}(t)X_{i}(t)\right] \right\}$$

$$= \frac{1}{\lambda m_{i}(t)^{2}} \left\{ E\left[Y_{i}^{2}(t)\right] + \left(r_{i}p_{i}\right)^{2} E\left[X_{i}^{2}(t)\right] - 2r_{i}p_{i}E\left[X_{i}(t)Y_{i}(t)\right] \right\}.$$

$$(4.9)$$

Hence, an approximate variance of the estimate of the number of units on node i

$$Var[\hat{r}_{i}(t)] \approx \frac{1}{p_{i}^{2}} \frac{1}{\lambda m_{i}(t)^{2}} \left\{ E[Y_{i}^{2}(t)] + (r_{i}p_{i})^{2} E[X_{i}^{2}(t)] - 2r_{i}p_{i}E[X_{i}(t)Y_{i}(t)] \right\}. \tag{4.10}$$

To approximate the variance of the sum of the estimates, a Taylor expansion vields

$$E\left[\frac{V_{i}(t)}{N_{i}(t)}\frac{V_{j}(t)}{N_{j}(t)}\right] = E\left[\frac{v_{i}(t) + Y_{i}(t)/\sqrt{\lambda}}{m_{i}(t) + X_{i}(t)/\sqrt{\lambda}} \frac{v_{j}(t) + Y_{j}(t)/\sqrt{\lambda}}{m_{j}(t) + X_{j}(t)/\sqrt{\lambda}}\right]$$

$$= \frac{v_{i}(t)v_{j}(t)}{m_{i}(t)m_{j}(t)} + \frac{1}{\lambda} \frac{1}{m_{i}(t)m_{j}(t)} E[Y_{i}(t)Y_{j}(t)]$$

$$-\frac{v_{i}(t)v_{i}(t)}{\lambda[m_{i}(t)m_{i}(t)]^{2}} E[X_{i}(t)X_{j}(t)] + o\left(\frac{1}{\lambda}\right)$$
(4.11)

for $i \neq j$.

Thus,

$$Cov(\hat{r}_{i}(t), \hat{r}_{j}(t)) = \frac{1}{p_{i}p_{j}}Cov\left(\frac{V_{i}(t)}{N_{i}(t)}, \frac{V_{j}(t)}{N_{j}(t)}\right)$$

$$\approx \frac{1}{\lambda} \frac{1}{p_{i}m_{i}(t)} \frac{1}{p_{i}m_{j}(t)} \left\{ E\left[Y_{i}(t)Y_{j}(t)\right] - r_{i}p_{i}r_{j}p_{j}E\left[X_{i}(t)X_{j}(t)\right] \right\}. \tag{4.12}$$

Expressions (4.10) and (4.12) can be used to approximate $Var\left[\sum_{i}\hat{r}_{i}(t)\right]$.

5. A Simpler Poisson Approximation

Assume the probability of allocation α_i is independent of $(V_i(t), N_i(t))$; then the number of looks at node i is a Poisson process with rate $\lambda \alpha_i$ independent of the other nodes. Further

$$E[N_i(t)] = 1 + \alpha_i t \tag{5.1}$$

$$E[V_i(t)] = r_i p_i [1 + \alpha_i t]$$
(5.2)

$$Var[N_i(t)] = \alpha_i t \tag{5.3}$$

$$Var[V_i(t)] = r_i p_i (1 - p_i) + \alpha_i t \left[r_i p_i (1 - p_i) + (r_i p_i)^2 \right]$$
 (5.4)

$$Cov[N_i(t), V_i(t)] = r_i p_i \alpha_i t \tag{5.5}$$

where we assume that at time 0 each node is looked at once.

In this case (4.10) becomes

$$Var[\hat{r}_i(t)] = \frac{1}{p_i^2} \frac{r_i p_i (1 - p_i)}{1 + \alpha_i t}.$$
 (5.6)

and the estimators $\hat{r}_i(t)$ are independent.

Assume purposeful allocation is adapted with function h_i as in (3.1). A simple approximation to $Var\left[\sum_i \hat{r}_i(t)\right]$ can be obtained by neglecting all covariances and

assuming the number of looks at node i, $\{N_i(t); t \ge 0\}$, is a Poisson process with rate $\lambda \alpha_i$ where α_i is determined by (3.6). In this case

$$Var\left[\sum_{i} \hat{r}_{i}(t)\right] \approx \sum_{i} \frac{1}{p_{i}} \frac{r_{i}(1-p_{i})}{(1+\alpha_{i}t)}.$$
(5.7)

6. Numerical Examples

Suppose there are 3 nodes with r_j units on node j with $r_1 = 49$, $r_2 = 25$, and $r_3 = 16$. The probabilities of detecting a unit on node j, p_j , are $p_1 = 1/11$, $p_2 = 0.5$, and $p_3 = 10/11$.

The variance of the estimate of the sum of the units on all the nodes under purposeful allocation with h_i as in (3.1) was studied using simulation for $\gamma = 0$, 1, 10. Each replication of the simulation begins with one observation at each node. The times of arrival of a Poisson process with rate 1 are then simulated. A node for observation at time t is randomly chosen using probabilities

$$\alpha_i(t) = K(t) \left[\frac{a_i}{N_i(t)} + \frac{V_i(t)(1-p_i)}{N_i(t)^2 p_i^2} \right]$$

for i = 1, 2, 3 with K(t) the normalizing constant. A binomial observation is generated for the node chosen. The simulation has 500 replications.

Table 1 records the sample mean and square root of the sample variance of the sum of the estimates $\sum_{i=1}^{3} \hat{r}_i(t)$ for t = 5, 10, 20, 50 where

$$\hat{r}_i(t) = \frac{V_i(t)}{N_i(t)p_i}.$$

Also shown are the sample means of the square root of the sum of estimated approximate variances (1.3)

$$\hat{\sigma}_{i}^{2}(t) = \frac{V_{i}(t)(1-p_{i})}{N_{i}(t)^{2}p_{i}^{2}}.$$

Table 1
Estimate of Total Number of Units on All Nodes $r_1 = 49, r_2 = 25, r_3 = 16; \ p_1 = 1/11, p_2 = 0.5, p_3 = 10/11$

			Simulation		Approximation					
			$\sum_{i}\hat{r}_{i}(t)$	$\sqrt{\sum_i \sigma_i^2(t)}$	Square Root of Differential	Square Root of Poisson				
Time	γ	Sample Mean	Square Root of Sample Variance	Sample Mean	Equation Approx Variance	Approx Variance				
5	0	89.8	18.0	15.0	13.9	13.9				
	1	88.1	15.1	10.7	12.3	10.7				
	10	89.3	15.2	10.9	12.5	10.4				
10	0	90.3	12.4	11.9	10.9	10.9				
	1	89.8	9.2	8.2	9.1	8.1				
	10	90.1	10.2	8.6	10.2	8.0				
20	0	90.0	8.9	8.6	8.2	8.2				
	1	89.5	7.1	6.1	6.7	6.0				
	10	89.5	8.3	6.5	8.0	6.1				
50	0	89.9	5.8	5.5	5.4	5.4				
	1	89.9	3.9	3.9	4.2	3.9				
	10	89.5	6.2	4.3	5.7	4.2				

Table 1 also displays results of the approximate variance $Var\left[\sum_{i}\hat{r}_{i}(t)\right]$ obtained using (4.10) and (4.12) and solving the differential equations (2.8) and the second moment equations in Appendix A, (A.27) – (A.32). The equations were solved numerically using the 4th/5th order Runge-Kutta-Fehlberg method as implemented in MATLAB; (cf. Math Works, 1992).

Table 1 also displays the simple Poisson approximation to $Var\left[\sum_{i}\hat{r}_{i}(t)\right]$ of (5.7) with the α_{i} in (3.6).

Recall that the estimate $Var\left[\sum_i\hat{r}_i(t)\right]$ is unbiased for both approximations. The true value of $\sum r_i$ is 90. The differential equation approximation is close to the square root of the sample variance for all values of γ for times 10, 20, and 50. The Poisson approximation is close to the square root of the sum of the estimated approximate variances; both of these approximations are neglecting the covariances induced by the purposeful allocation; these covariances become more pronounced as γ becomes larger. There is no covariance for $\gamma=0$, equally likely allocation. Note that the Poisson approximation is conservative. However for $\gamma=1$, the Poisson approximation is within about 10% of the differential equation approximation which incorporates the covariances. However the difference is larger for $\gamma=10$.

Note that the square root of the sample variance and the differential equation approximation suggest that purposeful allocation with $\gamma = 1$ yields the smallest variance of the estimated sum of the numbers of units on all the nodes. A rationale for this suggestion follows.

Suppose there are a fixed number of looks K that the sensor can take of all nodes and the number of units on each node i, r_i , is known along with the

probability of detecting a unit on node i, p_i . Let k_i be the number of looks the sensor gives to node i. If each observation has a binomial distribution

$$Var\left[\sum_{i=1}^{3} \hat{r}_{i}(t)\right] = \sum_{i=1}^{3} \frac{k_{i} r_{i} p_{i} (1 - p_{i})}{k_{i}^{2} p_{i}^{2}}$$
$$= \sum_{i=1}^{3} \frac{r_{i} (1 - p_{i})}{k_{i} p_{i}}.$$

Lagrange multipliers can be used to show that the (approximate) k_i , i = 1, 2, 3 that minimize $Var\left[\sum_{i=1}^{3} \hat{r}_i(t)\right]$ are $k_i = \left[r_i(1-p_i)/p_i\right]^{\frac{1}{2}}$. This solution corresponds to

the α_i of (3.6) with $a_i = 0$ and $\gamma = 1$. Thus, if one is interested in minimizing the estimated variance of the sum of the number of units on all the nodes, then one should look at node i a number of times proportional to $\left[r_i(1-p_i)/p_i\right]^{0.5}$. If one were interested in minimizing the estimated variance of the estimate of the number of units on the node with the greatest number of units then one would allocate all looks to that node; this corresponds to the purposeful allocation policy of $\gamma = \infty$.

Tables 2 and 3 present results of the simulation experiment with $r_1 = 49$, $r_2 = 25$, $r_3 = 16$ and $p_1 = 0.7$, $p_2 = 0.8$, and $p_3 = 0.9$. Table 2 presents the simulation and approximation results for the estimate of the sum of units on all the nodes. Table 3 presents the simulation and approximation results for the number of units on the individual nodes. The differential equation results are close to the simulated values for times t = 10, 20, 50. The Poisson approximation also seems to be adequate. The Poisson approximation may be doing better in this case because the probabilities of unit detection are larger. One source of the covariance between the estimators $\hat{r}_i(t)$ is the possibility that V(i, t) may be 0, in

which case node i will not be visited very frequently for $\gamma > 0$ for the purposeful allocation with function h_i as in (3.1).

Table 2 Estimate of Total Number of Units on All Nodes $r_1 = 49$, $r_2 = 25$, $r_3 = 16$; $p_1 = 0.7$, $p_2 = 0.8$, $p_3 = 0.9$

			Simulation		Approxima	ation
		2	$\sum_{i}\hat{r}_{i}(t)$	$\sqrt{\sum_i \sigma_i^2(t)}$	Square Root of Differential	Square Root of Poisson
Time	γ	Sample Mean	Square Root of Sample Variance	Sample Mean	Equation Approx Variance	Approx Variance
5	0	89.9	5.52	3.70	3.30	3.30
	1	89.4	6.53	3.15	3.11	3.02
	10	8 8.9	8.55	3.14	3.06	2.98
10	0	90.1	2.75	2.84	2.59	2.59
	1	89.9	2.37	2.45	2.46	2.35
	10	89.7	2.46	2.53	2.51	2.35
20	0	90.1	2.04	2.07	1.95	1.95
	1	90.0	1.72	1.80	1.90	1.76
	10	89.9	1.87	1.88	2.06	1.80
50	0	90.0	1.30	1.32	1.28	1.28
	1	90.0	1.12	1.17	1.29	1.16
	10	89.9	1.26	1.24	1.35	1.21

Table 3
Simulation: 500 replications
Estimate of Number of Units on Node

					G						20						10						5					Time			
					5						0				_						_							ne			
	10		-		0		10		1		0		10		-		0		10		1		0				,	≺			
	49.0		49.0		49.1		49.0		49.0		49.1		48.9		49.0		49.1		48.5		48.6		49.0					Mean			
(0.76)	0.77	(0.85)	0.88	(1.09)	1.08	(1.15)	1.16	(1.30)	1.32	(1.66)	1.68	(1.53)	1.57	(1.74)	1.81	(2.20)	2.33	(2.00)	4.85	(2.27)	3.95	(2.81)	3.89	Approx)	(Diff Eqtn	Variance	Sample	Square Root	$\hat{r}_i(t)$	Node 1	
(0.77)	0.77	(0.86)	0.86	(1.09)	1.12	(1.19)	1.19	(1.33)	1.32	(1.66)	1.75	(1.63)	1.61	(1.81)	1.81	(2.20)	2.39	(2.17)	2.12	(2.38)	2.37	(2.81)	3.11		Approx)	(Poisson	Mean	Sample	$\sqrt{\hat{\sigma}_i^2(t)}$		
	24.9		25.0		25.0		24.9		24.9		25.0		24.9		24.9		25.0		24.6		24.8		24.9					Mean			0.1.1
(0.72)	0.72	(0.63)	0.64	(0.59)	0.63	(1.08)	1.08	(0.96)	0.97	(0.90)	0.98	(1.44)	1.50	(1.27)	1.36	(1.20)	1.36	(1.88)	2.94	(1.62)	2.38	(1.53)	2.20	Approx)	(Diff Eqtn	Variance	Sample	Square Root	$\hat{r}_{i}(t)$	Node 2	
(0.70)	0.72	(0.63)	0.64	(0.59)	0.61	(1.05)	1.10	(0.95)	0.98	(0.90)	0.95	(1.37)	1.48	(1.25)	1.32	(1.20)	1.30	(1.70)	1.89	(1.59)	1.69	(1.53)	1.68		Approx)	(Poisson	Mean	Sample	$\sqrt{\hat{\sigma}_i^2(t)}$		
	16.0		16.0		16.0		15.9		16.0		16.0		15.9		16.0		16.0		15.8		16.0		16.0					Mean			
(0.66)	0.71	(0.45)	0.45	(0.32)	0.33	(1.00)	1.06	(0.68)	0.71	(0.48)	0.52	(1.29)	1.33	(0.89)	0.96	(0.64)	0.71	(1.33)	1.97	(1.07)	1.54	(0.82)	1.17	Approx)	(Diff Eqtn	Variance	Sample	Square Root	$\hat{r}_{\rm f}(t)$	Node 3	
(0.61)	0.65	(0.44)	0.46	(0.32)	0.32	(0.84)	0.95	(0.65)	0.71	(0.48)	0.50	(1.00)	1.26	(0.82)	0.93	(0.64)	0.68	(1.13)	1.32	(0.99)	1.13	(0.82)	0.87		Approx)	(Poisson	Mean	Sample	$\sqrt{\hat{\sigma}_i^2(t)}$		

REFERENCES

- P. J. Bickel and K. A. Doksum, "Mathematical Statistics: Basic Ideas and Selected Topics," Holden-Day, Inc., San Francisco, CA, 1977.
- D. P. Gaver and P. A. Jacobs, "Asymptotic properties of stochastic greedy bin-packing," *Stochastic Models*, **11** (1995) pp. 333-348.
- D. P. Gaver, J. A. Morrison, and R. Silveira, "Service-adaptive multitype repairman problems," SIAM J. Appl. Math., 53 (1993) pp. 454-470.
- P. Hall, "On the erratic behavior of estimators of N in the binomial N, p distribution," Journal of the American Statistical Association, 89 (1994) pp. 344-352.
- The Math Works, Inc., MATLAB Reference Guide, The Math Works, Inc., Natick, MA, August 1992.
- S. K. Thompson, and G. A. F. Seber, "Detectability in conventional and adaptive sampling," *Biometrics*, **50** (1994) pp. 712-725.

APPENDIX A

In the Appendix we present details of the normal approximation. We follow an analytical approach used in a different context in Gaver and Jacobs (1995), and in Gaver, Morrison, and Silveira (1993). Let the moment-generating function (assumed to exist, otherwise use the characteristic function) be

$$\psi(\boldsymbol{\theta}, \boldsymbol{\xi}; t) = E\left[\exp\left\{\boldsymbol{\theta}N(t) + \boldsymbol{\xi}V(t)\right\}\right]$$

$$= E\left[\exp\left\{\sum_{j=1}^{I} \theta_{j} N_{j}(t) + \sum_{j=1}^{I} \xi_{j} V_{j}(t)\right\}\right]. \tag{A.1}$$

Condition on $(N_i(t), V_i(t)), i \in \{1, 2, ..., I\}$ to obtain

$$E\left[\exp\left\{\sum_{j=1}^{I}\theta_{j}N_{j}(t+h)+\xi_{j}V_{j}(t+h)\right\}N(t),V(t)\right]$$

$$=(1-\lambda h)\exp\left\{\Theta N(t)+\xi V(t)\right\}$$

$$+\lambda h\sum_{i}\alpha_{i}(N(t),V(t))\exp\left\{\Theta N(t)+\xi V(t)\right\}\left[e^{\theta_{i}}\hat{b}(\xi_{i})\right]$$
(A.2)

where

$$\hat{b}(\xi_i) = E\left[e^{\xi_i Z(i)}\right]. \tag{A.3}$$

with Z(i) an observation of the number of units on node i.

Let $h \rightarrow 0$ to obtain

$$\frac{\partial}{\partial t}\psi(\boldsymbol{\theta},\boldsymbol{\xi};t) = -\lambda\psi(\boldsymbol{\theta},\boldsymbol{\xi};t) + \lambda\sum_{i=1}^{I} E\left[\alpha_{i}(N(t),V(t))\exp\{\boldsymbol{\theta}N(t) + \boldsymbol{\xi}V(t)\}e^{\theta_{i}}\hat{b}(\xi_{i})\right]. \quad (A.4)$$

Scaling

Let

$$X_{j}(t) = \frac{N_{j}(t) - \lambda m_{j}(t)}{\sqrt{\lambda}}$$
 (A.5)

$$Y_j(t) = \frac{V_j(t) - \lambda v_j(t)}{\sqrt{\lambda}}$$
 (A.6)

and let $\lambda \gg 1$.

Let

$$\varphi(\theta, \xi; t) = E[\exp\{\theta X(t) + \xi Y(t)\}]; \tag{A.7}$$

then

$$\psi(\theta/\sqrt{\lambda}, \xi/\sqrt{\lambda}; t) = \varphi(\theta, \xi; t) \exp\{\sqrt{\lambda} [\theta m(t) + \xi v(t)]\}. \tag{A.8}$$

Thus, we have the following equation from (A.8) and (A.4)

$$\frac{\partial}{\partial t} \psi \left(\boldsymbol{\theta} / \sqrt{\lambda}, \boldsymbol{\xi} / \sqrt{\lambda}; t \right)
= \frac{\partial}{\partial t} \varphi \left(\boldsymbol{\theta}, \boldsymbol{\xi}; t \right) \exp \left\{ \sqrt{\lambda} \left[\boldsymbol{\theta} \boldsymbol{m}(t) + \boldsymbol{\xi} \boldsymbol{v}(t) \right] \right\}
+ \sqrt{\lambda} \varphi \left(\boldsymbol{\theta}, \boldsymbol{\xi}; t \right) \exp \left\{ \sqrt{\lambda} \left[\boldsymbol{\theta} \boldsymbol{m}(t) + \boldsymbol{\xi} \boldsymbol{v}(t) \right] \right\} \left[\boldsymbol{\theta} \boldsymbol{m}'(t) + \boldsymbol{\xi} \boldsymbol{v}'(t) \right]
= \left[-\lambda \varphi \left(\boldsymbol{\theta}, \boldsymbol{\xi}; t \right) \right]
+ \lambda \sum_{i=1}^{I} E \left[\alpha_{i} \left(\boldsymbol{m}(t) + \frac{1}{\sqrt{\lambda}} \boldsymbol{X}(t), \boldsymbol{v}(t) + \frac{1}{\sqrt{\lambda}} \boldsymbol{Y}(t) \right) \exp \left\{ \boldsymbol{\theta} \boldsymbol{X}(t) + \boldsymbol{\xi} \boldsymbol{Y}(t) \right\} \right] e^{\theta_{i} / \sqrt{\lambda}} \hat{b}_{i} \left(\boldsymbol{\xi}_{i} / \sqrt{\lambda} \right) \right]
\times \exp \left\{ \sqrt{\lambda} \left[\boldsymbol{\theta} \boldsymbol{m}(t) + \boldsymbol{\xi} \boldsymbol{v}(t) \right] \right\}.$$
(A.9)

Dividing both sides by $\exp\{\sqrt{\lambda}[\theta m(t) + \xi v(t)]\}$ we obtain

$$\frac{\partial}{\partial t}\varphi(\theta,\xi;t) + \sqrt{\lambda}\varphi(\theta,\xi;t) \Big[\theta m'(t) + \xi v'(t)\Big]
= -\lambda\varphi(\theta,\xi;t)
+\lambda \sum_{i=1}^{I} E \left[\left\{ \alpha_{i}(m(t),v(t)) + \sum_{j} \frac{\partial}{\partial m_{j}} \alpha_{i}(m(t),v(t)) \frac{1}{\sqrt{\lambda}} X_{j}(t) \right. \right.
\left. + \sum_{j} \frac{\partial}{\partial \beta_{j}} \alpha_{i}(m(t),v(t)) \frac{1}{\sqrt{\lambda}} Y_{j}(t) + O\left(\frac{1}{\sqrt{\lambda}}\right) \right\} \exp\left\{\theta X(t) + \xi Y(t)\right\} \left[e^{\theta_{i}/\sqrt{\lambda}} \hat{b}_{i}(\xi_{i}/\sqrt{\lambda}) \right]$$
(A.10)

Let

$$\alpha_i(m(t), v(t)) = \frac{h_i(m_i(t), v_i(t))}{\sum_j h_j(m_j(t), v_j(t))}$$
(A.11)

where $h_j(x, y)$ is a sufficiently smooth function with first order partial derivatives and $h_j(\lambda^p x, \lambda^p y) = \lambda^p h_j(x, y)$.

Let

$$H_i(x;t) = \frac{\frac{\partial}{\partial m_i} h_i(m_i(t), v_i(t))}{\sum_j h_j(m_j(t), v_j(t))}$$
(A.12)

$$H_i(y;t) = \frac{\frac{\partial}{\partial v_i} h_i(m_i(t), v_i(t))}{\sum_j h_j(m_j(t), v_j(t))}$$
(A.13)

$$H_{ik}(x;t) = \frac{h_i(m_i(t), v_i(t))}{\left(\sum_j h_j(m_j(t), v_j(t))\right)^2} \frac{\partial}{\partial m_k} h_k(m_k(t), v_k(t))$$
(A.14)

$$H_{ik}(y;t) = \frac{h_i(m_i(t), v_i(t))}{\left(\sum_j h_j(m_j(t), v_j(t))\right)^2} \frac{\partial}{\partial v_k} h_k(m_k(t), v_k(t))$$
(A.15)

Note that

$$\alpha_i \left(\lambda m_i(t) + \sqrt{\lambda} X_i(t), \lambda v_i(t) + \sqrt{\lambda} Y_i(t) \right)$$

$$= \frac{h_i(m_i(t), v_i(t))}{\sum_{j=1}^{l} h_j(m_j(t), v_j(t))}$$
(A.16)

$$+\frac{1}{\sqrt{\lambda}}\left[H_i(x;t)X_i(t)+H_i(y;t)Y_i(t)+\sum_k H_{ik}(x;t)X_k(t)+\sum_k H_{ik}(y;t)Y_k(t)\right]+O\left(\frac{1}{\lambda}\right).$$

Since

$$\sum_{i} \alpha_{i} \left(\lambda m_{i}(t) + \sqrt{\lambda} X_{i}(t), \lambda v_{i}(t) + \sqrt{\lambda} Y_{i}(t) \right) = 1$$
(A.17)

this implies that the summed coefficients of $1/\sqrt{\lambda}$, $1/\lambda$ etc. must individually be 0.

Expression (A.10) can be rewritten as

$$\frac{\partial}{\partial t} \varphi(\boldsymbol{\theta}, \boldsymbol{\xi}; t) + \sqrt{\lambda} \varphi(\boldsymbol{\theta}, \boldsymbol{\xi}; t) [\boldsymbol{\theta} m'(t) + \boldsymbol{\xi} v'(t)]$$

$$= -\lambda \varphi(\boldsymbol{\theta}, \boldsymbol{\xi}; t)$$

$$+\lambda \sum_{i} \left[1 + \frac{\theta_{i}}{\sqrt{\lambda}} + \frac{b_{1}(i)\xi_{i}}{\sqrt{\lambda}} + \frac{1}{2} \frac{\theta_{i}^{2}}{\lambda} + \frac{1}{2} \frac{b_{2}(i)\xi_{i}^{2}}{\lambda} \right]$$

$$\times \left\{ \frac{h_{i}(m_{i}(t), v_{i}(t))}{\sum_{j} h_{j}(m_{j}(t), v_{j}(t))} \varphi(\boldsymbol{\theta}, \boldsymbol{\xi}; t)$$

$$+ \frac{1}{\sqrt{\lambda}} \left[H_{i}(x; t) \frac{\partial}{\partial \theta_{i}} \varphi(\boldsymbol{\theta}, \boldsymbol{\xi}; t) + H_{i}(y; t) \frac{\partial}{\partial \xi_{i}} \varphi(\boldsymbol{\theta}, \boldsymbol{\xi}; t) \right]$$

$$- \sum_{k=1}^{I} \left[H_{ik}(x; t) \frac{\partial}{\partial \theta_{k}} \varphi(\boldsymbol{\theta}, \boldsymbol{\xi}; t) + H_{ik}(y; t) \frac{\partial}{\partial \xi_{k}} \varphi(\boldsymbol{\theta}, \boldsymbol{\xi}; t) \right] + O\left(\frac{1}{\lambda}\right)$$
(A.18)

where $b_n(i) = E[Z(i)^n]$ the n^{th} moment of an observation at node i.

Let

$$\varphi(\boldsymbol{\theta}, \boldsymbol{\xi}; t) = \sum_{\ell=0}^{\infty} \varphi_{\ell}(\boldsymbol{\theta}, \boldsymbol{\xi}; t) \lambda^{-\ell/2}.$$
 (A.19)

Substituting (A.19) into (A.18) results in the following equation for φ_0

$$\begin{split} &\frac{\partial}{\partial t}\varphi_{0}(\boldsymbol{\theta},\boldsymbol{\xi};t)+\sqrt{\lambda}\,\varphi_{0}(\boldsymbol{\theta},\boldsymbol{\xi};t)\big[\boldsymbol{\theta}\boldsymbol{m}'(t)+\boldsymbol{\xi}\boldsymbol{v}'(t)\big]\\ &=-\lambda\varphi_{0}(\boldsymbol{\theta},\boldsymbol{\xi};t)\\ &+\lambda\sum_{i}\bigg[1+\frac{1}{\sqrt{\lambda}}\big(\boldsymbol{\theta}_{i}+b_{1}(i)\boldsymbol{\xi}_{i}\big)+\frac{1}{2}\frac{1}{\lambda}\big(\boldsymbol{\theta}_{i}^{2}+b_{2}(i)\boldsymbol{\xi}_{i}^{2}\big)\bigg]\\ &\times\Bigg\{\frac{h_{i}(m_{i}(t),v_{i}(t))}{\sum_{j}h_{j}\big(m_{j}(t),v_{j}(t)\big)}\varphi_{0}(\boldsymbol{\theta},\boldsymbol{\xi};t)\\ &+\frac{1}{\sqrt{\lambda}}\bigg[H_{i}(x;t)\frac{\partial}{\partial\boldsymbol{\theta}_{i}}\varphi_{0}(\boldsymbol{\theta},\boldsymbol{\xi};t)+H_{i}(y;t)\frac{\partial}{\partial\boldsymbol{\xi}_{i}}\varphi_{0}(\boldsymbol{\theta},\boldsymbol{\xi};t)\\ &-\sum_{k=1}^{I}\bigg[H_{ik}(x;t)\frac{\partial}{\partial\boldsymbol{\theta}_{k}}\varphi_{0}(\boldsymbol{\theta},\boldsymbol{\xi};t)+H_{ik}(y;t)\frac{\partial}{\partial\boldsymbol{\xi}_{k}}\varphi_{0}(\boldsymbol{\theta},\boldsymbol{\xi};t)\bigg]\bigg]\Bigg\}+O\bigg(\frac{1}{\lambda}\bigg). \end{split} \tag{A.20}$$

Equating terms of order $\lambda^{\ell/2}$, the terms of order λ cancel. The terms of order $\sqrt{\lambda}$ result in the equation

$$\varphi_{0}(\boldsymbol{\theta},\boldsymbol{\xi};t)[\boldsymbol{\theta}m'(t)+\boldsymbol{\xi}v'(t)]$$

$$=\sum_{i=1}^{I} \left\{ \frac{h_{i}(m_{i}(t),v_{i}(t))}{\sum_{j} h_{j}(m_{j}(t),v_{j}(t))} \varphi_{0}(\boldsymbol{\theta},\boldsymbol{\xi};t)[\boldsymbol{\theta}_{i}+b_{1}(i)\boldsymbol{\xi}_{i}] + H_{i}(x;t) \frac{\partial}{\partial \theta_{i}} \varphi_{0}(\boldsymbol{\theta},\boldsymbol{\xi};t) + H_{i}(y;t) \frac{\partial}{\partial \xi_{i}} \varphi_{0}(\boldsymbol{\theta},\boldsymbol{\xi};t) + H_{i}(y;t) \frac{\partial}{\partial \xi_{k}} \varphi_{0}(\boldsymbol{\theta},\boldsymbol{\xi};t) + H_{i}(y;t) \frac{\partial}{\partial \xi_{k}} \varphi_{0}(\boldsymbol{\theta},\boldsymbol{\xi};t) \right\} + O\left(\frac{1}{\lambda}\right). \tag{A.21}$$

The terms of order $\sqrt{\lambda}$ cancel if

$$\Theta m'(t) + \xi v'(t) = \sum_{i=1}^{I} \frac{h_i(m_i(t), v_i(t))}{\sum_{j} h_j(m_j(t), v_j(t))} [\theta_i + b_1(i)\xi_i]. \tag{A.22}$$

In order for this to occur

$$\frac{d}{dt}m_{i}(t) = \frac{h_{i}(m_{i}(t), v_{i}(t))}{\sum_{j} h_{j}(m_{j}(t), v_{j}(t))} \quad i = 1, \dots I$$
(A.23)

and

$$\frac{d}{dt}v_{i}(t) = b_{1}(i)\frac{h_{i}(m_{i}(t), v_{i}(t))}{\sum_{j} h_{j}(m_{j}(t), v_{j}(t))} \quad i = 1, \dots I.$$
(A.24)

Thus,

$$v_i(t) = b_1(i)m_i(t)$$
. (A.25)

Next look for terms of order 1 in (A.20).

$$\frac{\partial}{\partial t} \varphi_{0}(\boldsymbol{\theta}, \boldsymbol{\xi}; t) \\
= \sum_{i} \frac{h_{i}(m_{i}(t), v_{i}(t))}{\sum_{j} h_{j}(m_{j}(t), v_{j}(t))} \left[\frac{1}{2} \theta_{i}^{2} + \frac{1}{2} b_{2}(i) \xi_{i}^{2} + b_{1}(i) \theta_{i} \xi_{i} \right] \varphi_{0}(\boldsymbol{\theta}, \boldsymbol{\xi}; t) \\
+ \sum_{i} \left[H_{i}(x; t) \frac{\partial}{\partial \theta_{i}} \varphi_{0}(\boldsymbol{\theta}, \boldsymbol{\xi}; t) + H_{i}(y; t) \frac{\partial}{\partial \xi_{i}} \varphi_{0}(\boldsymbol{\theta}, \boldsymbol{\xi}; t) \right] \left[\theta_{i} + b_{1}(i) \xi_{i} \right] \\
+ \sum_{i} \sum_{k} \left[H_{ik}(x; t) \frac{\partial}{\partial \theta_{k}} \varphi_{0}(\boldsymbol{\theta}, \boldsymbol{\xi}; t) + H_{ik}(y; t) \frac{\partial}{\partial \xi_{k}} \varphi_{0}(\boldsymbol{\theta}, \boldsymbol{\xi}; t) \right] \left[\theta_{i} + b_{1}(i) \xi_{i} \right]. \tag{A.26}$$

Equations for the joint moments of $\{(X_j(t), Y_j(t))\}$ can be obtained by differentiating (A.26) with respect to $\{\theta_i\}$ and $\{\xi_i\}$ and evaluated at $\theta = \xi = 0$. The resulting equations are

$$\frac{d}{dt} E[X_{\ell}^{2}(t)]$$

$$= \frac{h(m_{\ell}(t), v_{\ell}(t))}{\sum_{j} h(m_{j}(t), v_{j}(t))} + 2H_{\ell}(x;t)E[X_{\ell}(t)^{2}] + 2H_{\ell}(y;t)E[X_{\ell}(t)Y_{\ell}(t)] \qquad (A.27)$$

$$+2\sum_{k} H_{\ell k}(x;t)E[X_{\ell}(t)X_{k}(t)] + 2\sum_{k} H_{\ell k}(y;t)E[X_{\ell}(t)Y_{k}(t)]$$

For $\ell \neq a$

$$\frac{d}{dt}E[X_{\ell}(t)X_{a}(t)]
= H_{a}(x;t)E[X_{a}(t)X_{\ell}(t)] + H_{a}(y;t)E[Y_{a}(t)X_{\ell}(t)]
+ H_{\ell}(x;t)E[X_{a}(t)X_{\ell}(t)] + H_{\ell}(y;t)E[X_{a}(t)Y_{\ell}(t)]
+ \sum_{k} H_{ak}(x;t)E[X_{k}(t)X_{\ell}(t)] + \sum_{k} H_{ak}(y;t)E[X_{\ell}(t)Y_{k}(t)]
+ \sum_{k} H_{\ell k}(x;t)E[X_{a}(t)X_{k}(t)] + \sum_{k} H_{\ell k}(y;t)E[X_{a}(t)Y_{k}(t)].$$
(A.28)
$$\frac{d}{dt}E[Y_{\ell}^{2}(t)] = \frac{h(m_{\ell}(t), v_{\ell}(t))}{\sum_{j} h(m_{j}(t), v_{j}(t))} b_{2}(\ell)
+ 2b_{1}(\ell)[H_{\ell}(x;t)E[X_{\ell}(t)Y_{\ell}(t)] + H_{\ell}(y;t)E[Y_{\ell}^{2}(t)]]
+ 2b_{1}(\ell)\sum_{i} H_{\ell j}(x;t)E[X_{j}(t)Y_{\ell}(t)] + H_{\ell j}(y;t)E[Y_{\ell}(t)Y_{j}(t)]$$

For $j \neq k$

$$\frac{d}{dt}E[Y_{k}(t)Y_{j}(t)] = \{H_{j}(x;t)E[X_{j}(t)Y_{k}(t)] + H_{j}(y;t)E[Y_{j}(t)Y_{k}(t)]\}b_{1}(j)
+ \{H_{k}(x;t)E[X_{k}(t)Y_{j}(t)] + H_{k}(y;t)E[Y_{j}(t)Y_{k}(t)]\}b_{1}(k)
+ b_{1}(j)\sum_{\ell}H_{j\ell}(x;t)E[X_{\ell}(t)Y_{k}(t)] + H_{j\ell}(y;t)E[Y_{k}(t)Y_{\ell}(t)]
+ b_{1}(k)\sum_{\ell}H_{k\ell}(x;t)E[X_{\ell}(t)Y_{j}(t)] + H_{k\ell}(y;t)E[Y_{\ell}(t)Y_{j}(t)]
\frac{d}{dt}E[X_{k}(t)Y_{k}(t)]
= \frac{h_{k}(m_{k}(t),v_{k}(t))}{\sum_{j}h_{j}(m_{j}(t),v_{j}(t))}b_{1}(k)
+ H_{k}(x;t)\{E[Y_{k}(t)X_{k}(t)] + E[X_{k}^{2}(t)]b_{1}(k)\}
+ H_{k}(y;t)[E[Y_{k}^{2}(t)] + E[X_{k}(t)Y_{k}(t)]b_{1}(k)]
+ \sum_{j}\{H_{kj}(x;t)E[X_{j}(t)X_{k}(t)] + H_{kj}(y;t)E[X_{k}(t)Y_{j}(t)]\}b_{1}(k)$$

$$+\sum_{j}\{H_{kj}(x;t)E[X_{j}(t)X_{k}(t)] + H_{kj}(y;t)E[X_{k}(t)Y_{j}(t)]\}b_{1}(k)$$
(A.31)

For $\ell \neq k$

$$\frac{d}{dt} E[X_{\ell}(t)Y_{k}(t)]
= H_{\ell}(x;t) E[X_{\ell}(t)Y_{k}(t)] + H_{\ell}(y;t) E[Y_{\ell}(t)Y_{k}(t)]
+ \{H_{k}(x;t) E[X_{\ell}(t)X_{k}(t)] + H_{k}(y;t) E[X_{\ell}(t)Y_{k}(t)]\} b_{1}(k)
+ \sum_{j} H_{\ell j}(x;t) E[X_{j}(t)Y_{k}(t)] + H_{\ell j}(y;t) E[Y_{k}(t)Y_{j}(t)]
+ \sum_{j} \{H_{k j}(x;t) E[X_{j}(t)X_{\ell}(t)] + H_{k j}(y;t) E[Y_{j}(t)X_{\ell}(t)]\} b_{1}(k)$$
(A.32)

INITIAL DISTRIBUTION LIST

1.	Research Office (Code 08)
2.	Dudley Knox Library (Code 52)
3.	Defense Technical Information Center
4.	Director, Force Structure, Resources and Assessment (J-8)
5.	Deputy Director for Technical Operations, J-8
6.	Chief, Warfare Analysis Division, J-8
7.	Prof. Donald P. Gaver (Code OR/Gv)
8.	Prof. Patricia A. Jacobs (Code OR/Jc)
9.	Prof. Mark Youngren (Code OR/Ym)5 Naval Postgraduate School Monterey, CA 93943-5000
10.	Prof. George Connor (Code OR/Co)
11.	Prof. Michael Sovereign (Code OR/Sm)
12.	Ms. Therese Bilodeau (Code OR/Bi)

13.	Dr. J. Abrahams, Code 1111, Room 607
14.	Dr. John Bailar
15.	Prof. D. R. Barr
16.	Dr. David Brillinger
17.	Dr. David Burman
18.	Prof. Brad Carlin
19.	Dr. Robert Carpenter
20.	Center for Naval Analyses
21.	Prof. H. Chernoff Department of Statistics Harvard University 1 Oxford Street Cambridge, MA 02138
22.	Mr. Wm. P. Clay Director, USAMSAA Attn: AMXSY-CA APG, MD 21005-5071
23.	Dr. Edward G. Coffman, Jr. AT&T Bell Telephone Laboratories 600 Mountain Avenue Murray Hill, NJ 07974

24.	Dept. of Mathematics, University of Birmingham P. O. Box 363 Birmingham B15 2TT ENGLAND
25.	Professor Sir David Cox
26.	Professor H. G. Daellenbach
27.	Dr. S. R. Dalal
28.	Dr. D. F. Daley
29.	Dr. B. Doshi
30.	Dr. Naihua Duan
31.	Prof. Bradley Efron
32.	Dr. Guy Fayolle
33.	Dr. Andrew Gelman

34.	Dr. Neil Gerr
	Office of Naval Research
	Arlington, VA 22217
	Arington, VA 22217
35.	Prof. Peter Glynn
	Dept. of Operations Research
	Stanford University
	Stanford, CA 94350
	Statuoru, CA 7550
	· · · · · · · · · · · · · · · · ·
36.	Prof. Bernard Harris
	Dept. of Statistics
	University of Wisconsin
	610 Walnut Street
	Madison, WI 53706
37.	Prof. J. Michael Harrison
57.	Graduate School of Business
	Stanford University
	Stanford, CA 94305-5015
38.	Dr. P. Heidelberger1
	IBM Research Laboratory
	Yorktown Heights
	New York, NY 10598
	14ew 101k,141 10000
39.	Dr. D. C. Hoaglin
37.	
	Department of Statistics
	Harvard University
	1 Oxford Street
	Cambridge, MA 02138
4 0.	Prof. D. L. Iglehart1
	Dept. of Operations Research
	Stanford University
	Stanford, CA 94350
	Statuora, CA 34330
44	Total to Co Defense Analysis
41.	Institute for Defense Analysis
	1800 North Beauregard
	Alexandria, VA 22311
42 .	Prof. J. B. Kadane1
	Dept. of Statistics
	Carnegie-Mellon University
	Pittsburgh, PA 15213
	110000000000000000000000000000000000000
4 3.	Dr. F. P. Kelly
43.	
	Statistics Laboratory
	16 Mill Lane
	Cambridge
	ENGLAND

44.	Dr. Jon Kettenring
45.	Koh Peng Kong
46.	Prof. Guy Latouche
47.	Dr. A. J. Lawrance
48.	Prof. M. Leadbetter
49.	Prof. J. Lehoczky
50.	Dr. James R. Maar
51.	Dr. Colin Mallows
52.	Prof. R. Douglas Martin
53.	Prof. M. Mazumdar

54.	Dr. James McKenna
	Morristown, NJ 07960-1910
55.	Prof. Paul Moose
56.	Prof. Carl N. Morris
57.	Dr. John A. Morrison
58.	Prof. F. W. Mosteller
59.	Operations Research Center, Rm E40-164
60.	Dr. T. J. Ott
61.	Dr. Jim Petty
62.	Dr. V. Ramaswami
63.	Dr. Martin Reiman

64.	Prof. Maria Rieders
	Dept. of Industrial Eng.
	Northwestern Univ.
	Evanston, IL 60208
65.	Dr. Rhonda Righter
	Dept. of Decision & Info. Sciences
	Santa Clara University
	Santa Clara, CA 95118
66.	Dr. John E. Rolph
	RAND Corporation
	1700 Main St.
	Santa Monica, CA 90406
	Salita Molina, CA 70400
(7	Part Paral Consular
67.	Prof. Frank Samaniego
	Statistics Department
	University of California
	Davis, CA 95616
68.	Prof. W. R. Schucany
00.	Dept. of Statistics
	Southern Methodist University
	Dallas, TX 75222
69.	Prof. G. A. F. Seber
	Dept. of Statistics
	Univ. of Auckland
	Private Bag 92019
	Auckland, NEW ZEALAND
7 0.	Prof. G. Shantikumar
, 0.	The Management Science Group
	School of Business Administration
	University of California
	Berkeley, CA 94720
71.	Prof. D. C. Siegmund
	Dept. of Statistics
	Sequoia Hall
	Stanford University
	Stanford, CA 94305
7 2.	Prof. N. D. Singpurwalla
	George Washington University
	Washington, DC 20052
<i>7</i> 3.	Prof. H. Solomon
	Department of Statistics
	Sequoia Hall
	Stanford University
	Stanford, CA 94305

74.	Dr. Andrew Solow
75 .	Prof. W. Stuetzle
76.	Prof. J. R. Thompson
77.	Prof. Steven K. Thompson
7 8.	Prof. J. W. Tukey
7 9.	Dr. D. Vere-Jones
80.	Prof. David L. Wallace
81.	Dr. Ed Wegman
82.	Dr. Alan Weiss
83.	Dr. P. Welch
84.	Prof. Roy Welsch